



## DIGITAL MULTIMETER

**Model : DM 321 T**

### STANDARD ACCESSORIES

- 3 1/2 Digits
- TRUE RMS
- Manual Ranging WITH HOLSTER AUTO POWER OFF
- DATA HOLD & BACK LIGHT
- A/V CONTINUITY TEST
- Auto Rang. CAPACITANCE Test
- Tr., hFE TEST

### SPECIFICATIONS

- **DC Voltage :**  
**Range** 200 mV, 2 V, 20 V, 200 V, 1000 V  
**Basic Accuracy**  $\pm (0.5 \% \text{ rdg} + 3 \text{ digits})$
- **AC voltage (TRUE RMS) :**  
**Range** 2 V, 20 V, 200 V, 750 V  
**Basic Accuracy**  
 $\pm (0.8 \% \text{ rdg} + 5 \text{ digits})$   
Freq. Response : 40 ~ 400 Hz (750 V Range : 40 ~ 200 Hz)
- **DC current :**  
**Range** 20 pA, 2 mA, 20mA, 200 mA, 20 A  
**Basic Accuracy**  $\pm (0.8\% \text{ rdg} + 10 \text{ digits})$
- **AC current (TRUE RMS):**  
**Range** 20mA, 200 mA, 20 A  
**Basic Accuracy**  
 $\pm(1.0\% \text{ rdg}+ 15 \text{ digits})$   
Freq. Response : 40 ~ 200 Hz
- **Resistance :**  
**Range** 200  $\Omega$ , 2 K  $\Omega$ , 20 K  $\Omega$ , 200 K  $\Omega$ , 2 M  $\Omega$ , 20 M  $\Omega$   
**Basic Accuracy**  $\pm (0.8\% \text{ rdg} + 3 \text{ digits})$
- **Capacitance :**  
**Range** 2 nF~ 20mF  
**Basic Accuracy**  $\pm (2.5 \% \text{ rdg} + 20 \text{ digits})$
- **DCV & ACV Input Impedance :** 10 M $\Omega$
- **Transistor Test :** hFE (PNP or NPN)
- **Continuity Test & Diode Test :** Provided
- **Other Facilities / Features :** Auto Power Off. Low Batt, Indication
- **Accessories Supplied :** Test Leads, User Manual & Battery (Installed / Kept Aside)
- **Dimension & Weight :** 175 x 93 x 55 mm & Approx. 400 gms. (incl. Batt.)

